

CODE	DESCRIPTION
OPEN	Check the closure of the porthole and relating indicator in case it is open
E1	Display shows the safety device for water loss has tripped
E2	Overflow engaged (only out of a washing program)
E4	Water temperature probe in short circuit or interrupted
E5	As water is being loaded, if the pressure switch does not reach the full level within the first 6', the display shows the problem
E6	If during water drain, the empty level is not reached in 12', the display shows the problem.
E10	Motor over-current
E11	Problem of motor control triac (short circuit or interrupted)
E12	Indication for tachymetry mal-functioning.
E13	Mal functioning of door block PTC
E14	Dryer temperature probe in short circuit or interrupted
E-	Communication problem between interface board and mother board.
E-	Board hardware problem